

24V 12W Power Supply and PoE Injector with LEDs

EZ-BP1224

The new **EZ-BP1224** Power Supply and PoE Injector with LEDs is made from TPEE material in an aesthetic package and is available with two RJ45 ports to act as “Data-In” and “PoE+Data out”.

The new **EZ-BP1224** indoor PoE Injector allows you to use your space efficiently when installing your wireless equipment through the smart desk top case.

The Red LED indicates the adapter is powered up.



Features :

- Fast and easy desktop case.
- All-In-One Power Supply and POE Injector Included.

TECHNICAL SPECIFICATIONS

Input Condition	AC100~240V 50/60Hz 0.6A max
Input Rated Voltage	100Vac~200Vac
Input Voltage Rate	90Vac~264Vac
Input Rated Frequency	50/60Hz
Input Frequency Range	47Hz~63Hz
Input Current	0.6A Max
Input Inrush Current	30A Max
Input No Load Power Consumption	0.5 Watt Max @ 115Vac/230Vac
Efficiency	80% Min
Rated Output Voltage & Current	24V/0.5A
Output Line Regulation	+/-1%
Output Load Regulation	+/-5%
Output Over Shoot	10% Max
Output Ripple and Noise	1% Max
Output Rising Time	20ms Max @ 115Vac
Output Hold-Up Time	8ms Min @ 230Vac
Protection	OCP OVP SCP OPP
Dielectric Withstand Voltage	3KV 5mA 60s
Leakage Current	0.25mA @ 230Vac
Dimension	89x70x32mm
Weight	75 gr (Without AC cable)
Operating Temperature Range	0°C~40°C
Storage Temperature Range	-20°C~+85°C
AC Cable	Choice of EU, UK or US AC Cable
Certifications	CE / UL / GS / RoHS / EMC
Origin	China

Additional Images



24V 12W Power Supply and PoE Injector with LEDs

EZ-BP1224

Dimensions

