

MaxLink PR22


Parabolic antenna

Gain	22dBi
B to F ratio	>30db
Directivity	10°
SWR	<1,5
Diameter	320mm
Weight	1,2kg
Frequency	5,3- 5,8GHz
Polarization	horizonal/vertical
Impedance	50Ω
Connector	N female
Pole diameter	28-66mm
Optional kit	Radom



Diagrams

Directionality



SWR

